



MERCURY APPLICATION GUIDE

Mercury Application Guide

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rectifier Regulator	Harness
4	40	2	72-75	3296137-4107219	R336-4516*	174-4469 LS 174-4470 HS	POINTS	N/A	N/A
4	Gnat	2	76-80	9075839-5595531	114-6222	174-6120K1	N/A	N/A	N/A
4	40	2	80	5589202-5595531	114-6222	174-6120K1	N/A	N/A	N/A
4	-	2	80-89	5595532 - A855096	R336-4516*	174-4469 LS 174-4470 HS	POINTS	N/A	N/A
4.5	-	2	75-80	4107220-5595531	R336-4516*	174-4469 LS 174-4470 HS	POINTS	N/A	N/A
6	-	2	86-96	A197112-OG289100	114-7452K1	174-6617K1	R98450A10*	N/A	N/A
6	-	2	97-00	OG760300-OG830999	114-5713	174-5721K1	R98450A10*	N/A	N/A
7.5	75	2	70-71	2810637-3274632	IN STATOR	174-3996	POINTS	N/A	N/A
7.5	75	2	72-73	3274633-3801457	R336-4516*	174-4469 LS 174-4470 HS	POINTS	N/A	N/A
7.5	75	2	74-86	3801458-A197111	114-6222	174-6120K1	R338-5286 A6	154-6770	N/A
8	-	2	86-96	A197112-OG289100	114-7452K1	174-6617K1	R98450A5*	N/A	N/A
8	-	2	97-00	OG760300-OG830999	114-5713	174-5721K1	R98450A10*	N/A	N/A
9.8	110	2	66-71	1865779-3263262	IN STATOR	174-3996	POINTS	N/A	N/A
9.8	110	2	72-73	3263263-3795658	R336-4516*	174-4469 LS 174-4470 HS	POINTS	N/A	N/A
9.8	110	2	74-78	3795659-5206549	114-6222	174-6120K1	338-7283A2	154-6770	N/A
9.8	-	2	79-85	5206550-6620196	114-6222	174-6120K1	338-7283A2	N/A	N/A
9.9	-	2	86-96	A197112-OG289100	114-7452K1	174-6617K1	R98450A5*	N/A	N/A
9.9	-	2	97-00	OG760300-OG830999	114-5713	174-5721K1	R98450A10*	N/A	N/A
10	-	2	86-96	A197112-OG289100	114-7452K1	174-6617K1	R98450A5*	N/A	N/A
10	-	2	97-00	OG760300-OG830999	114-5713	174-5721K1	R98450A10*	N/A	N/A
15	S15	2	88-93	B238464-OG044365	114-7452K1	174-6617K1	R98450A5*	N/A	N/A
15	XD/S15	2	94-96	OG044027-OG437999	114-4952K1	174-6617K1	R98450A5*	154-6770	N/A
15	XD/S15	2	96-97	OG438000-OG760299	114-7452K1	174-6617K1	R98450A5*	154-6770	N/A
15	Sea Pro	2	96-97	OG438000-OG760299	114-7452K1	174-6617K1	R98450A5*	154-6770	N/A
15	Comm	2	97-00	OG760300-OG830999	114-5713	174-5721K1	R98450A10*	154-6770	R84-1233A2*
15	-	2	97-00	OG760300-OG830999	114-5713	174-5721K1	R98450A10*	154-6770	R84-1233A2*
18	-	2	80-93	5837437-OG044026	114-7452A3	174-6617K1	R98450A1*	N/A	R84-88891A1*
18	XD	2	79-87	5837437-B114230	114-7452A3	174-6617K1	R98450A1*	N/A	R84-88891A1*
20	200	2	70-71	2827677-3226957	IN STATOR	174-3996	POINTS	N/A	N/A
20	200	2	72-73	3226958-3537530	R336-4516*	174-4469 LS 174-4470 HS	POINTS	N/A	N/A
20	200	2	73-77	3537531-4709592	114-4911	174-4991 LS 174-4992 HS	R339-4996A1	N/A	N/A
20	-	2	77-81	4709593-5837436	114-6222	174-6120K1	R74324A3*	N/A	N/A
20	XD	2	79-87	5837437-B114230	114-7452A3	174-6617K1	R98450A1*	N/A	N/A
20	-	2	80-87	5705532 - B238463	114-7452K1	174-6617K1	R98450A5*	N/A	N/A
20	-	2	80-87	5705532 - B238463	114-7452A3	174-6617K1	R98450A1*	N/A	N/A
20	-	2	88-94	B238464-OG044026	114-7452K1	174-6617K1	R98450A1*	N/A	R84-88891A1*
20	-	2	94-96	OG044027-OG437999	114-4952k1	174-6617K1	R98450A5*	154-6770	N/A
20	Sea Pro	2	96-97	OG438000-OG760299	114-7452K1	174-6617K1	R98450A5*	154-6770	N/A
20	-	2	97-98	OG438000-OG760299	114-4952K1	174-6617K1	R98450A5*	154-6770	N/A
20	Comm	2	98-2000	OG760300	114-5713	174-5721K1	R98450A10*	154-6770	R84-1233A2*
20	-	2	98-2000	OG760300	114-5713	174-5721K1	R98450A10*	154-6770	R84-1233A2*
25	XD	2	79-87	5837437-B114230	114-7452A3	174-6617K1	R98450A1*	N/A	R84-88891A1*
25	-	2	79-87	5705532 - OB238463	114-7452A3	174-6617K1	R98450A1*	N/A	N/A
25	-	2	79-87	5705532 - OB238463	114-7452K1	174-6617K1	R98450A5*	N/A	N/A
25	-	2	88-93	OB238464-OG044365	114-7452K1	174-6617K1	R98450A5*	N/A	N/A
25	Jet 20	2	94-97	OG044027-OG437999	114-4952K1	174-6617K1	R98450A5*	154-6770	N/A
25	Sea Pro	2	96-97	OG438000-OG760299	114-7452K1	174-6617K1	R98450A5*	154-6770	N/A
30	Elect Start	2	94-96	OG053314-OG380074	114-7509	R398-832074A5*	134-9021-2	194-5279	R84-830574A2
30	Elect Start	2	97-99	OG380075-OG590100	114-7509	R398-832074A4*	134-4512-3	194-5279	R84-830574A2
30	Man. Start	3	98-99	OG590000-OG760299	114-7509	R398-832074A5*	134-4512-3	N/A	N/A
30	Elect Start	3	98-99	OG590000-OG760299	114-7509	R398-832074A4*	134-4512-3	194-5279	N/A
30	Man. Start	3	99-00	OG760300	114-7509	R398-832074A5*	134-4512-3	N/A	N/A
30	Elect Start	3	99-00	OG760300	114-7509	R398-832074A4*	134-4512-3	194-5279	414-0220A5
30	JET	4	89-97	C159200-OG589999	114-5772	174-5454K1	134-6452	154-6770	414-8672
35	-	2	84-89	6445653-B393190	114-7452A3	174-6617K1	R98450A1	154-6770	414-6219A 8
35	-	2	84-89	6445653-B393190	114-7452K1	174-6617K1	R98450A5	N/A	414-6219A 2
40	400ElcStrt.	2	70-71	2874704-3336237	R332-4172	174-4424	N/A	154-6770	414-2770
40	400MnStrt.	2	70-71	2874704-3336237	R332-4172	174-4424	N/A	N/A	N/A
40	402ElcStrt.	2	72-74	3336258-3859434	R338-4733	174-5255	R338-4731A6*	154-6770	414-2770

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.

MERCURY



MERCURY APPLICATION GUIDE

MERCURY

Mercury Application Guide (Cont.) Mercury Application Guide

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rectifier Regulator	Harness
40	402MnStrt.	2	72-74	3336258-4117709	114-4911	174-5255	R338-4731A6*	N/A	N/A
40	402ElcStrt.	2	75-77	4117710-4860102	114-4911	174-5255	R338-4731A6*	154-6770	414-2770
40	Man.Start	2	75-81	4117710-5823917	114-4911	174-5255	R338-4731A6*	N/A	N/A
40	Elect.Start	2	78-81	4860103 - 5823917	114-4911	174-5255	R338-4731A6*	154-6770	414-2770
40	Elect.Start	2	81-84	5823918-6052942	114-7452A3	174-6617K1	R92431A1*	154-6770	R84-93948A1*
40	Elect.Start	2	81-84	6052943-6999999	114-7452A3	174-6617K1	R92431A1*	154-6770	414-6219A 2
40	Man.Start	2	81-84	5823918-6999999	114-7452A3	174-6617K1	R92431A1*	N/A	N/A
40	Elect.Start	4	89-91	C159200 - D055047	114-5772	174-5454K1	134-6452	154-6770	414-8672A 8
40	Man.Start	4	89-91	C159200 - D055047	114-5772	174-5454K1	134-6452	N/A	N/A
40	Elect.Start	4	91-96	D055048-OG291031	114-5772	174-9710K1	134-6452	194-5279	414-8672A 8
40	-	3	97-99	OG531301-OG760299	114-7509	R398-832074A5*	N/A	N/A	N/A
40	Elect.Start	3	97-99	OG531301-OG760299	114-7509	174-2075K1	134-4512-3	194-5279	414-0220A 2
40	Jet	4	89-97	C159200 - OG589999	114-5772	174-5454K1	134-6452	154-6770	414-8672A 8
45	Elect.Start	4	81-89	5531630-B393190	114-5772	174-5454K1	134-6452	154-6770	414-6277
45	Man.Start	4	81-89	5531630-B393190	114-5772	R76314A3	134-6452	N/A	N/A
45	Jet	3	91-99	D000750-OG589999	114-9052	174-9710K1	134-9021-3	194-5279	414-9061
50	500	4	67	2116318-2305100	114-2986	R398-2996	R393-2918A1*	154-6770	414-2770
50	Elect.Start	4	70-75	2858814-4357639	R333-3213*	174-3175 (RED) 174-3176 (BLUE)	IGN DRIVER	154-6770	414-2770
50	Elect.Start	4	76-79	4357640-5531629	114-5772	174-5454K1	134-6452	154-6770	414-3369
50	Man.Start	4	76-79	4357640-5531629	114-5772	R76314A3*	134-6452	N/A	N/A
50	Elect.Start	4	80-85	5531630-6586624	114-5772	174-5454K1	134-6452	154-6770	414-6277
50	Man.Start	4	80-85	5531630-6586624	114-5772	R76314A3*	134-6452	N/A	N/A
50	-	3	84-90	6428681-D000749	114-7778	174-5454K1	134-6453	154-6770	414-4614A1
50	-	3	91-99	D000750-OG589999	114-9052	174-9710K1	134-9021-3	194-5279	414-4614A1
50	Man.Start	3	97-99	OG531301-OG760300	114-7509	R398-832074A5*	N/A	N/A	N/A
50	Elect.Start	3	97-00	OG531301-OG833000	114-7509	174-2075K2	N/A	194-5279	414-0220A2
55	-	3	91-99	D000750-OG589999	114-9052	174-9710K1	134-9021-3	194-5279	414-9061
55	Elect.Start	3	96-98	G290585-OG589999	114-9052	174-9710K1	134-9021-3	N/A	N/A
55	Man.Start	3	96-98	G290585-OG589999	114-9052	R398-9873A33*	134-9021-3	N/A	N/A
60	-	3	84-90	6428681-D000749	114-7778	174-5454K1	134-6453	154-6770	414-4614A1
60	-	3	91-97	D000750-OG589999	114-9052	174-9710K1	134-9021-3	194-5279	414-9061
60	-	3	97-00	OG531301-OG833000	114-7509	174-2075K1	N/A	194-5279	414-0220A2
65	650	4	67	2119749-2309310	114-2986	R398-2997*	R393-2918A1*	154-6770	414-2770
65	650	4	68	2309311-2452709	R333-3213*	174-3175 (RED) 174-3176 (BLUE)	IGN DRIVER	154-6770	414-2770
65	-	4	69-71	2503991-3293183	114-2986	174-4793	R393-2918A1*	154-6770	414-2770
65	-	3	72-75	3293184-4382056	114-4796	R398-4634*	R332-4797	154-6770	R84-60795*
65	-	3	76-79	4382057-4571651	114-7778	174-5454K1	134-6453	154-6770	R84-73204*
65	Jet ElcStrt	3	94-96	D283222-OG437999	114-4953	174-9710K1	134-9021-3	194-5279	414-1591
65	JetManStrt	3	94-96	D283222-OG437999	114-4953	R398-9873A33*	134-9021-3	N/A	N/A
65	Jet	3	96-99	OG438000-OPO17000	114-7509	174-2075K1	R834820T	194-5279	414-0043
70	-	3	77-87	4571652-A730815	114-7778	174-5454K1	134-6453	154-6770	R84-73204*
70	9 Amp	3	87-93	A996142 - D283221	114-7778	174-8778K1	134-9021-3	154-6770	414-1591
70	16 Amp	3	87-93	A996142 - D283221	114-7778	174-9710K1	134-9021-3	194-5279	414-1591
75	-	4	84-88	6432901-B279480	114-5772	174-5454K1	134-6454	154-6770	414-6233A2
75	9 Amp	3	87-93	A996142 - D283221	114-7778	174-8778K1	134-9021-3	154-6770	414-1591
75	16 Amp	3	87-93	A996142 - D283221	114-7778	174-9710K1	134-9021-3	194-5279	414-1591
75	Elect.Start	3	94-96	D283222-OG437999	114-4953	174-9710K1	134-9021-3	194-5279	414-1591
75	Man.Start	3	94-96	D283222-OG437999	114-4953	R398-9873A33*	134-9021-3	N/A	N/A
75	-	3	96-00	OG438000-OG850499	114-7509	174-2075K2	834820T**	194-5279	414-0043
80	800	4	69	2559001-2991033	114-2986	174-4793	134-3736	154-6770	414-2770
80	800	4	70	3051041-3052380	R337-4411*	174-4793	**337-4406	154-6770	414-2770
80	800	4	70	3052381-3059820	114-2986	174-4793	134-3736	154-6770	414-2770
80	800	4	71	3144219-3192962	114-2986K1	174-4793	134-3736	154-6770	414-2770
80	800	4	71-72	3307347-3493912	114-2986	174-4793	134-3736	154-6770	414-2770
80	-	4	78-79	4831999-5582561	114-5772	174-5454K1	134-6452	154-6770	414-3369
80	-	4	80-83	5582562-6432900	114-5772	174-5454K1	134-6454	154-6770	414-6233A2
80	9 Amp	3	87-93	A996142 - D283221	114-7778	174-8778K1	134-9021-3	154-6770	414-1591
80	16 Amp	3	87-93	A996142 - D283221	114-7778	174-9710K1	134-9021-3	154-6770	414-1591

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



MERCURY APPLICATION GUIDE

Mercury Application Guide (Cont.) Mercury Application Guide

HP	Model	Cyl	Year	Serial Number	Switch Box	Stator	Trigger	Rectifier Regulator	Harness
85	850	4	73-75	3493913-4366801	114-2986	174-4793	134-3736	154-6770	414-2770
85	850	4	76-77	4366802-4831998	114-5772	174-5454K1	134-6452	154-6770	414--3369
90	Inline	6	78-79	4845301-5299505	114-2986	174-4793	134-3736	154-6770	414-2770
90	Inline	6	79-86	5299506 - B110053	114-7778	174-5456	134-6456	154-6770	R84-96188A4*
90	Elect.Start	3	87-92	A996142 - C221999	114-7778	174-8778K1	134-9021-3	154-6770	414-1591
90	Elect.Start	3	93-96	C222000-OG437999	114-4953	174-9710K1	134-9021-3	194-5279	414-1591
90	Man.Start	3	94-96	D283222-OG437999	114-4953	R398-9873A33*	134-9021-3	N/A	N/A
90	-	3	96-99	OG438000-OP017000	114-7509	174-2075K2	R854512T*	194-5279	414-0043
90	Sport Jet	3	95	E021000-E095087	114-7778	174-8778K1	134-7029-3	194-5279	414-6075
90	Sport Jet	3	95-96	E080400-E145579	114-4953	174-8778K1	134-7029-3	194-5279	414-6075
95	950 Inline	6	66-67	1869776-2101742	114-2803	R398-2188*	POINTS	N/A	414-2770
95	950	6	66-67	2101743-2318585	114-2986	R398-2188*	134-3736	154-6770	414-2770
95	XRSprtJet	3	95-97	E141089 - E315900	114-4953	174-9710K1	134-7029-3	194-5279	R84-828297A2*
100	1000 Inline	6	67-69	2641855-3253111	114-2986	R398-3633*	393-2918A1*	154-6770	414-2770
100	-	4	88-93	B209468 - D283221	114-5772	174-8778K1	134-9021-4	194-5279	414-3443
100	9 Amp	4	94-96	D283222-OG437999	114-5772	174-8778K1	134-9021-4	194-5279	414-3443
100	16 Amp	4	94-96	D283222-OG437999	114-5772	174-9710K1	134-9021-4	194-5279	414-3443
105	Jet	6	92-95	D082000 - OG201874	114-7778	174-9610K2	134-6456	194-5279	414-6220A16
105	Jet	6	96-00	OG303046-OG840500	114-7778	174-9610K2	134-6456	194-5279	R84-826730A4*
110	1100 Inline	6	66-67	1962462-2103722	114-2803	R398-2188*	POINTS	R32177A1*	414-2770
110	1100 Inline	6	67	2113898-2314955	114-2986	R398-2188*	134-3736	154-6770	414-2770
115	150 SSInline	6	70-79	2836019-5314655	114-2986	174-4793	134-3736	154-6770	414-2770
115	Inline	6	79-80	5314656-5600966	114-7778	174-5456	134-6456	154-6770	414-5532
115	Inline	6	80-82	5600967-6051525	114-7778	174-5456	134-6456	154-6770	R84-89564A1*
115	Inline	6	82-89	6051526-C10000	114-7778	174-5456	134-6456	154-6770	R84-96188A2*
115	9 Amp	4	89-93	C100000-D252460	114-5772	174-8778K1	134-9021-4	194-5279	414-3443
115	16 Amp	4	89-97	C100000-OG437999	114-5772	174-9710K1	134-9021-4	194-5279	R84-43443A3*
120	Sport Jet	4	95-96	E080400-E145579	114-6866	174-9710K1	134-7029-4	194-5279	414-6075
120	XRSportJet	4	95-97	E141089-E315900	114-7509	174-2075K2	134-8303-4	194-5279	R84-828297A2
125	1250 Inline	6	68-69	2314956-3253111	114-2986	R398-3587*	R393-2918	154-6770	414-2770
125	9 Amp	4	94-96	D283222-OG437999	114-5772	174-8778K1	134-9021-4	194-5279	414-3443
125	16 Amp	4	94-96	D283222-OG437999	114-5772	174-9710K1	134-9021-4	194-5279	414-3443
135	1350 Inline	6	70-71	2839369-3293233	114-2986	R398-3587*	134-3736	154-6770	414-2770
135	-	6	85-88	A904646-C100860	114-7778	174-5456-16	134-6456	154-6770	414-6220A4
135	-	6	89-90	C100861-C239552	114-7778	174-9610K2	134-6456	194-8736K1(A)	414-6220A12
135	16 Amp	6	90-91	C239553-D081999	114-7778	174-5456-16	134-6456	154-6770	414-6220A4
135	40 Amp	6	90-91	C239553-D081999	114-7778	174-9610K2	134-6456	194-8736K1(A)	414-6220A12
135	40 Amp	6	92-95	D082000-OG201874	114-7778	174-9610K2	134-6456	194-5279	414-6220A16
135	40 Amp	6	96-00	G303046-G840500	114-7778	174-9610K2	134-6456	194-5279	R84-826730A4*
140	1400 Inline	6	72	3293234-3502805	114-2986	174-4793	134-3736	154-6770	414-2770
140	Inline	6	78-79	4855153-5314655	114-2986	174-4793	134-3736	154-6770	414-2770
140	Inline	6	79	5327663-5625107	114-7778	174-5456-16	134-6456	154-6770	414-5532
140	-	6	80	5625108-5669999	114-7778	174-5456	134-6456	154-6770	R84-89564A1*
140	Jet	6	92-95	D082000-OG201874	114-7778	174-9610K2	134-6456	194-5279	414-6220A16
140	Jet	6	96-99	OG303046-OG760300	114-7778	174-9610K2	134-6456	194-5279	R84-826730A4*
150	1500 Inline	6	73-77	3502806-4868997	114-2986	174-4793	134-3736	154-6770	414-2770
150	XR2 Mag	6	78-86	4868998-OA904645	114-7778	174-5456	134-6456	154-6770	414-6220A4
150	-	6	85-88	A904646-C100860	114-7778	174-5456-16	134-6456	154-6770	414-6220A4
150	-	6	89-90	C100861-C239552	114-7778	174-9610K2	134-6456	194-8736K1(A)	414-6220A12
150	16 Amp	6	90-91	C239553-D081999	114-7778	174-5456-16	134-6456	154-6770	414-6220A4
150	40 Amp	6	90-91	C239553-D081999	114-7778	174-9610K2	134-6456	194-8736K1(A)	414-6220A12
150	40 Amp	6	92-95	D082000-OG201874	114-7778	174-9610K2	134-6456	194-5279	414-6220A16
150	40 Amp	6	96-00	OG303046-OG840500	114-7778	174-9610K2	134-6456	194-5279	R84-826730A4*
175	Black Max	6	76-79	4301235-5393736	114-7778	174-5456	134-6456	154-6770	414-6220A4
175	Black Max	6	79-84	5593737-6618750	114-7778	174-5456	134-6456	154-6770	414-6220A4
175	9 Amp	6	85-88	6618751-C100860	114-7778	174-5456	134-6456	154-6770	414-6220A4
175	15 Amp	6	85-88	6618751-C100860	114-7778	174-5456-16	134-6456	154-6770	414-6220A4
175	40 Amp	6	89-90	C100861-C239552	114-7778	174-9610K2	134-6456	194-8736K1(A)	414-6220A12
175	16 Amp	6	90-91	OC239553-OD081999	114-7778	174-5456-16	134-6456	154-6770	414-6220A4
175	40 Amp	6	90-91	OC239553-OD081999	114-7778	174-9610K2	134-6456	194-8736K1(A)	414-6220A12

MERCURY

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



MERCURY APPLICATION GUIDE

MERCURY

Mercury Application Guide (Cont.) Mercury Application Guide

HP	Model	Cyl.	Year	Serial Number	Switch Box	Stator	Trigger	Rectifier Regulator	Harness
175	XRi EFI 40 Amp	6	92-95	OD082000-OG201874	114-7778	174-9610K2	134-6456	194-5279	414-6220A16
175	XRi EFI 40 Amp	6	96-00	OG303046-OG840500	114-7778	174-9610K2	134-6456	194-5279	R84-826730A4*
175	XR2 Sport Jet	6	97-99	OE151580-OE345000	114-4953-32	174-9873-16	134-6456-15	194-5279	R84-832102A2*
200	Black Max	6	78-79	4839034 - 5363917	114-7778	174-5456	134-6456	154-6770	414-6220A4
200	Black Max	6	79-81	5363918-6073191	114-7778	174-5456	134-6456	154-6770	R84-87266A1*
200	15 Amp	6	82-90	6073192-C239553	114-7778	174-5456-16	134-6456	154-6770	414-6220A4
200	16 Amp	6	85-90	6625221-C239553	114-7778	174-5456-16	134-6456	194-5279	414-6220A4
200	16 Amp	6	89-95	C100861-OG201874	114-7778	174-5456-16	134-6456	154-6770	414-6220A4
200	XRi 40 Amp	6	89-91	C100861-OG303045	114-7778	174-9610K2	134-6456	194-8736K1(A)	414-6220A12
200	16 Amp	6	92-99	D082000-OG201874	114-7778	174-5456-16	134-6456	194-5279	414-6220A16
200	40 Amp	6	89-91	OG201875-OG30345	114-7778	174-9610K2	134-6456	194-8736K1(A)	R84-826730A4*
200	EFI	6	92-99	D082000-OG840500	114-7778	174-9610K2	134-6456	194-5279	414-6220A16
200	EFI	6	00-01	OG960500-OH000000	114-7509	R858454T 3*	134-6456-18	194-5279	R84-857166T1*
220	-	6	87-88	B117316-C100860	114-7778	174-5456-16	134-6456	154-6770	R84-92432A6*
225	-	6	81-93	5628028-D280812	114-7778	174-5456-16	134-6456	154-6770	N/A
225	3.0L	6	93-94	D280813-OG129221	114-7509K1	R821935A3*	N/A	Alternator	R84-825433A7*
225	3.0L	6	94-95	OG129222-OG303045	114-7509K1	R821935A5*	N/A	Alternator	N/A
225	3.0L	6	96-00	OG303046-OG840500	114-7509	R821935A5*	N/A	Alternator	N/A
250	3.0L	6	94-95	OG129222-OG303045	114-7509K1	R821935A5*	N/A	Alternator	N/A
250	3.0L	6	96-00	OG303046-OG840500	114-7509	R821935A5*	N/A	Alternator	N/A
250	2.5L	6	89-94	C101891-D280900	114-7778	174-5456-16	R89004A7*	154-6770	R84-92432A6*
250	16 Amp 40 Amp	6	89-94	C101891-D280900	114-7778	174-9610K2	R89004A7*	194-8736K1(A)	R84-92432A6*
250	XB 3.0L	6	00-01	OG980600-OH000000	114-7509	R821935A5*	N/A	Alternator	R84-825433A11*
275	16 Amp	6	89-94	C101891-D280900	114-7778	174-5456-16	R89004A7*	154-6770	R84-92432A6*
275	40 Amp	6	89-94	C101891-D280900	114-7778	174-9610K2	R89004A7*	194-8736K1(A)	R84-92432A6*
300	3.4L	6	80-87	5611648-A996135	114-7778	174-5456-16	R89004A5*	154-6770	R84-92432A1*

(A) The regulator/rectifier conversion kit requires a stator with 4 yellow wires. If your stator only has 2 yellow wires, please order P/N 174-9610A18.

* Indicates an item available on a Repair & Return basis at this time.

**Quick
Strike
Ignitions™**



**CDI
ELECTRONICS**