



JOHNSON/EVINRUDE APPLICATION GUIDE

MODEL TO YEAR IDENTIFICATION FOR 1980 and NEWER ENGINES

I N T R O D U C E S
1 2 3 4 5 6 7 8 9 0

(For example a J175CXEES is a 1999 175 HP engine)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & RPM	Stator	Rect/Reg	Trigger	Harness	Ign Coil
4	-	77-84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
4	Manual Start	85	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
4	RDH	89	2	113-4488 Conversion Kit	173-1670	N/A	133-3387	N/A	183-2508
4	-	93	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-3740
4	Comm	94-96	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
4	Deluxe	95	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
4.5	-	85	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
5	Elect Start	85	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
5	Manual Start	85	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
5	DR, RC ,RL, BA	89-90	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
5	-	91-92	2	113-4488 Conversion Kit	173-1670	R173692*	133-3387	N/A	183-2508
5	-	93-97	2	113-2285 CD2 NO LIMIT	173-1670	R173692*	133-3387	N/A	183-3740
5	DR, RE ,RL, SR	97	2	113-2285 CD2 NO LIMIT	173-1670	R173692*	133-3387	N/A	183-3740
5	DR	98	2	113-2285 CD2 NO LIMIT	173-1670	R173692*	133-3387	N/A	183-3740
5	RS, RL	2000	2	N/A	R5030217*	N/A	N/A	N/A	**584451
5	4 Stroke	97	2	N/A	R445016*	N/A	N/A	N/A	**584451
5	4 Stroke	2000	2	**440211 CD2 LIMITED	R445128*	N/A	**445018	N/A	**584451
6	-	77-84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
6	Manual Start	1985	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
6	Elect Start	1985	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
6	-	89-90	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
6	-	91-92	2	113-4488 Conversion Kit	173-1670	R173692*	133-3387	N/A	183-3740
6	-	94-00	2	113-2285 CD2 NO LIMIT	173-1670	R173692*	133-3387	N/A	183-3740
6	4 Stroke	2000	2	**440211 CD2 LIMITED	R445128*	N/A	**445018	N/A	**584451
6.5	Comm	89-90	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
8	Manual Start	85	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
8	Elect Start	85	2	113-3241 CD2 5800 L	173-1670	153-1778	133-3387	N/A	183-2508
8	-	89-90	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
8	-	91-92	2	113-4488 Conversion Kit	173-1670	R173692*	133-3387	N/A	183-3740
8	DR/RE/RL/SR	94-97	2	113-2285 CD2 NO LIMIT	173-1670	R173692*	133-3387	N/A	183-3740
8	RE/RL/RS	98-03	2	113-2285 CD2 NO LIMIT	173-1670	R173692*	133-3387	N/A	183-3740
8	RV/RX	98-03	2	113-2285 CD2 NO LIMIT	173-1670	R173692*	133-3387	N/A	183-3740
8	Comm	94-01	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-3740
8	4Stroke,El St.	95	2	N/A	R584821*	193-4890	IN PACK	N/A	**584451
8	4Stroke,Mn St	96	2	N/A	R445016*	N/A	IN PACK	N/A	**584451
8	4 Stroke,El St	96	2	N/A	R445016*	R445114*	IN PACK	R445099*	**584451
8	Manual Start	96	2	N/A	R445016*	N/A	IN PACK	N/A	**584451
8	4 Stroke,El St.	97	2	N/A	R445016*	R445114*	IN PACK	R445099*	**584451
8	4 Stroke,El St	2000	2	**440211 CD2 LIMITED	R445128*	N/A	**445018	N/A	**584451
9.9	Manual Start	77-82	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
9.9	Elect Start	77-83	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	133-3387	N/A	183-2366
9.9	Manual Start	83-84	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2366
9.9	Elect Start	84	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2366
9.9	Elect Start	85	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
9.9	-	88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
9.9	-	89-91	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	R584067*	183-3740
9.9	-	92	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	R584382*	183-3740
9.9	-	93	2	113-4783 CD2 NO LIMIT	173-1651	153-4597	133-3387	N/A	183-3740
9.9	-	94	2	113-4783 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-3740
9.9	Manual Start	95	2	113-4783 CD2 NO LIMIT	173-1670	N/A	**584716	N/A	183-3740
9.9	Elect Start	95	2	113-4783 CD2 NO LIMIT	173-1651	153-4597	IN STATOR	N/A	183-3740
9.9	Manual Start	96-05	2	113-4783 CD2 NO LIMIT	173-1670	N/A	**584716	N/A	183-3740
9.9	Elect Start	96-05	2	113-4783 CD2 NO LIMIT	173-1651	153-4597	IN STATOR	R586025*	183-3740
9.9	4 Stroke,Mn St	95-01	2	**586136 CD2 OPTICAL	173-4954	N/A	IN PACK	R585235*	**584451
9.9	4 Stroke,El St	95-01	2	**586505 CD2 OPTICAL	173-4954	193-4890	IN PACK	R586141*	**584451
10	-	85-88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
10	Comm	89-90	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
10	Kero, Com	90	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

J/E

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack/ Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
10	Comm	94	2	113-4783 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
10	4 Stroke	96-98	2	**586505 CD2 OPTICAL	173-4954	193-4890	IN PACK	R586141*	**584451
11	Comm	87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
14	-	88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
14	-	89-90	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
15	Manual Start	77-82	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
15	Elect Start	77-83	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	133-3387	N/A	183-2508
15	Manual Start	83-84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
15	Sail	83	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	R389399*	183-2508
15	Elect Start	84	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2366
15	-	88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
15	-	89-91	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	R584067*	183-2508
15	-	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584382*	183-3740
15	-	93	2	113-4783 CD2 NO LIMIT	173-1651	153-4597	133-3387	N/A	183-3740
15	-	94	2	113-4783 CD2 NO LIMIT	173-1670	N/A	**584716	N/A	183-3740
15	Elect Start	95	2	113-4783 CD2 NO LIMIT	173-1651	153-4597	IN STATOR	N/A	183-3740
15	BA, Man Star	95-05	2	113-4783 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-3740
15	Manual Start	95-05	2	113-4783 CD2 NO LIMIT	173-1670	N/A	**584716	N/A	183-3740
15	Elect Start	96-97	2	113-4783 CD2 NO LIMIT	173-1651	153-4597	IN STATOR	R586025*	183-3740
15	Comm	2000	2	113-4783 CD2 NO LIMIT	173-1670	N/A	**584716	N/A	183-3740
15	4 Strk,Man.Str	95	2	**584554 CD2 OPTICAL	R584614*	N/A	IN PACK	N/A	**584451
15	4 Stroke,El St	95	2	**584554 CD2 OPTICAL	173-4954	153-5081	IN PACK	N/A	**584451
15	4 Strk Mn St	96-98	2	**586136 CD2 OPTICAL	R584614*	N/A	IN PACK	N/A	**584451
15	4 Strk,El St	96-98	2	**586136 CD2 OPTICAL	173-4954	153-5081	IN PACK	R586141*	**584451
15	4 Strk, Mn St	2000	2	**586136 CD2 OPTICAL	173-4954	N/A	IN PACK	N/A	**584451
15	4 Strk,El St	2000	2	**586505 CD2 OPTICAL	173-4954	153-5081	IN PACK	N/A	**584451
18	Jet, 25 JRE	95-97	2	113-4767 CD2 SL6100	173-1670	N/A	133-3387	N/A	183-3740
20	Manual Start	77-84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
20	Elect Start	77-81	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	IN STATOR	413-9914	183-2366
20	Elect Start	82-84	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	413-1818	183-2366
20	Manual Start	85-88	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
20	Elect Start	85-88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R582524*	183-2508
20	Manual Start	89-91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
20	Elect Start	89-92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583648*	183-2508
20	EE, EL, IE, SE	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-2508
20	Manual Start	93-97	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-2508
20	Elect Start	93-95	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	R584881*	183-2508
20	Elect Start	96-97	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	413-0016	183-2508
20	Jet	2000	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	413-0016	183-2508
25	Elect Start	77	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	IN STATOR	R387872*	183-2366
25	Manual Start	77-84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	N/A	N/A	183-2366
25	Elect Start	78-81	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	IN STATOR	413-9914	183-2366
25	Elect Start	82-84	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	413-1818	183-2366
25	Manual Start	85-88	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
25	Elect Start	85-87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R582524*	183-2508
25	Elect Start	88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583601*	183-2508
25	Manual Start	89-92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
25	DR, DE, DT	89	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583705*	183-2508
25	EE, EL, IE, SE	89-91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583648*	183-2508
25	TL	90	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583649*	183-2508
25	TE, TTL	90	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584082*	183-2508
25	TE, TTL	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584216*	183-2508
25	TL	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584218*	183-2508
25	TL, M,El St	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
25	TL, J	92	2	113-5316 CD2 SL 6700	173-4560	193-4476	133-5386	413-4686	183-3740
25	EE, EL, IE, SE	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
25	TE, TTL (M)EIS	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584216*	183-3740
25	TTL, TE (J)EIS	92	2	113-5316 CD2 SL 6700	173-4560	193-4476	133-5386	R584695*	183-3740
25	Manual Start	93-97	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-2508

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack/ Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
25	Elect Start	93-95	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	R584881*	183-2508
25	TE	93-97	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	N/A	183-2508
25	TE	2000	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	N/A	183-2508
25	D, TL Elect St	93-95	2	113-4767 CD2 SL 6100	173-1670	R585035	**585072	413-4398	183-2508
25	Manual Start	96	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-2508
25	Elect Start	96	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	413-0016	183-2508
25	TNT	96	3	**584823 CD3 OPTICAL	R584821*	193-4890	N/A	R586043*	**584826
25	Manual Start	97	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-2508
25	Elect Start 2 STK	97-05	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	413-0016	183-2508
25	TEL/TNT	97-01	3	**584823 CD3 OPTICAL	R584821*	193-4890	N/A	R586043*	**584826
25	Manual Start	2000	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	413-0016	183-2508
25	Comm	82	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
25	Comm	83-84	2	113-2474 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-2366
25	Comm	85-88	2	113-3241 CD2 5800 L	173-1670	153-1778	133-3387	N/A	183-2508
25	Comm	89-90	2	113-4488 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
25	Comm	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
25	Comm	92-97	2	113-3241 CD2 5800 L	173-1670	N/A	**585072	N/A	183-2508
25	Comm	94	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	N/A	183-2508
25	Comm	95	2	113-3241 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-2508
25	H25FP Comm	95-97	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
25	Comm	97	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-2508
25	Comm	99-05	2	113-3241 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-2508
25	SIK, SIL, SIT	94-95	3	113-4808 CD3 AL 6700	173-4560	193-4476	N/A	413-4401	183-2508
25	Manual Start	96-97	3	**584823 CD3 OPTICAL	R176278*	**584952	**584824	N/A	**584826
25	AC, Man Start	96-97	3	**584823 CD3 OPTICAL	R584954*	**584952	**584824	R586091*	**584826
25	Elect Start	96-97	3	**584823 CD3 OPTICAL	R584821*	193-4890*	**584824	R586044*	**584826
25	A, R, RL	2000	3	**586472 CD3 OPTICAL	R584954*	N/A	**584824	R586091*	**584826
25	E, EL, PL, TEL	2000	3	**586472 CD3 OPTICAL	R584821*	193-4890	**584824	R586044*	**584826
28	Elect Start	85-87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R582524*	183-2508
28		88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583601*	183-2508
28	Manual Start	89	2	113-4489 Conversion Kit	173-1670	N/A	133-3387	N/A	183-2508
28	Elect Start	89-91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583648*	183-2508
28	SPL	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-2508
28	-	93-95	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	R584881*	183-2508
28	ES	96	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	413-0016	183-2508
28	JET, 40 JRE	95-98	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-3740
28	Manual Start	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
28	Elect Start	85-87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R582524*	183-2508
28	Manual Start	86-88	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
28	Manual Start	84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
30	Elect Start	84	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	413-1818	183-2366
30	Manual Start	85	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
30	Elect Start	85-86	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R582524*	183-2508
30	Elect Start	87-88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583601*	183-2508
30	Manual Start	88	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
30	Manual Start	89-92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
30	Elect Start	89-91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583648*	183-2508
30	TE	92	2	113-4489 Conversion Kit	173-1670	N/A	133-3387	N/A	183-2508
30	EE, EL, IE, SE	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-2508
30	Manual Start	93-97	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-2508
30	TE	93-97	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	N/A	183-2508
30	Elect Start	93-95	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	R584881*	183-2508
30	Elect Start	96-00	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	413-0016	183-2508
30	Manual Start	2000	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	413-0016	183-2508
30	JET	2000	2	113-3241 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-2508
35	-	76	2	N/A	N/A	N/A	POINTS	R386720*	N/A
35	Manual Start	77-84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

J/E

Application Guide (Cont.) Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
35	Elect Start	77-81	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	In Stator	413-9914	183-2366
35	Elect Start	82-84	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	413-1818	183-2366
35	Manual Start	85-88	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
35	Elect Start	85-87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R582524*	183-2508
35	Elect Start	87-88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583601*	183-2508
35	Manual Start	89-92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
35	Elect Start	89-91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583648*	183-2508
35	TE	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
35	Manual Start	93-97	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-2508
35	Manual Start	96-97	3	**584823 CD3 OPTICAL	173-4954	R584952*	N/A	N/A	**584826
35	Elect Start	96-97	3	**584823 CD3 OPTICAL	R584821*	193-4890	N/A	R586044*	**584826
35	TEL	96-97	3	**584823 CD3 OPTICAL	R584821*	193-4890	N/A	R586045*	**584826
35	TNT	96-97	3	**584823 CD3 OPTICAL	R584821*	193-4890	N/A	R586043*	**584826
35	A, R, RL	2000	3	**586472 CD3 OPTICAL	173-4954	N/A	**584824	R586091*	**584826
35	E, EL	2000	3	**586472 CD3 OPTICAL	R584821*	193-4890	**584824	R586044*	**584826
35	PL	2000	3	**586472 CD3 OPTICAL	R584821*	193-4890	**584824	R586043*	**584826
35	TEL	2000	3	**586472 CD3 OPTICAL	R584821*	193-4890	**584824	R586045*	**584826
35	JET, TL, M, EI St	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
35	Manual Start	1992	2	113-4489 Conversion Kit	173-1670	N/A	133-3387	N/A	183-3740
35	JET, TE, TTL, M	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-3740
35	JET, TL, J, EI St	92-93	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4695	183-3740
35	JET, EL, TL	93-95	2	113-4767 CD2 SL 6700L	173-1670	193-4476	133-3387	413-4695	183-3740
35	JET, TE, TTL, M	93-95	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4695	183-3740
35	-	1995	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R584686*	183-3740
35	JET, EL, TL, TTL	1996	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R586020*	183-3740
35	JET, Elect Start	1997	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R586020*	183-3740
35	JET, Man Start	1997	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-3740
40	Lark	69-70	2	N/A	N/A	N/A	POINTS	413-3326	N/A
40	Big Twin	69-70	2	N/A	N/A	N/A	POINTS	413-3325	N/A
40	-	1971	2	N/A	N/A	N/A	POINTS	R383324*	N/A
40	-	1972	2	N/A	N/A	N/A	POINTS	R385126*	N/A
40	-	1973	2	N/A	N/A	N/A	POINTS	R385895*	N/A
40	-	74-76	2	N/A	N/A	N/A	POINTS	413-6336	N/A
40	Manual Start	1984	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	413-9915	183-2366
40	Elect Start	1984	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	413-9915	183-2366
40	Manual Start	1985	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
40	Elect Start	1985	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583099*	183-2508
40	-	86-87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583211*	183-2508
40	-	1988	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583602*	183-2508
40	BA, EC, EL, RC, RL	1989	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-3649	183-3740
40	TE, TL, TTL	1989	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-3649	183-3740
40	TL	1990	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-3649	183-3740
40	TE, TTL	1990	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584082*	183-3740
40	TE, TTL	1991	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584216*	183-3740
40	TL	1991	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584218*	183-3740
40	BA, EE, EL	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4686	183-3740
40	RE, RL, J	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4686	183-3740
40	BA, EE, EL, (M)	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
40	RE, RL(M)	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
40	Manual Start	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-3740
40	TE, TTL, J	1992	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4695	183-3740
40	TE, TTL, M, EI St	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584216*	183-3740
40	TE	1992	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-3740
40	TL, M, Elect Start	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
40	Manual Start	93	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-3740
40	EL, TL	93-94	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4686	183-3740
40	TE, TTL	93-95	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4695	183-3740

* Indicates an item available on a Repair & Return basis at this time.
 ** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

Application Guide (Cont.) Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
40	Manual Start	94-95	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	N/A	183-3740
40	TE, TL, Elct Start	95	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4686	183-3740
40	Manual Start	96	2	113-4767 CD2 SL 6100	173-1670	153-1778	133-3387	N/A	183-3740
40	EL, TL, TTL, TE	96	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R586020*	183-3740
40	Manual Start	97	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-3740
40	Elect Start	97	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R586020*	183-3740
40	JPL	99	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	R586021*	183-3740
40	Manual Start	00	2	113-3241 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-3740
40	Elect Start 2 STK	00-05	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R585015*	183-3740
40	Comm	83-84	2	113-2474 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-2366
40	Comm	86	2	113-3241 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-2508
40	Comm	90	2	113-4488 Conversion Kit	173-1670	N/A	133-3387	N/A	183-3740
40	Comm, El Start	85	2	113-3241 CD2 5800L	173-1670	153-1778	133-3387	R583099*	183-2508
40	Comm, Man. Strt	85	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-2508
40	Comm	93	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-3740
40	Comm	96	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-3740
40	Comm	97	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-3740
40	Comm, Mn Start	94-95	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-3740
45	SS	88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583602*	183-2508
45	-	88	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
45	SS	89-90	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
45	Comm	85	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-2508
45	Comm	86	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
45	Comm	87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
45	Comm, Mn Start	89-90	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
45	Comm, El Start	89-90	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583948*	183-2508
45	Comm, El Start	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584386*	183-3740
45	Comm, Mn Start	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
45	Comm	92	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-3740
45	Comm	93-00	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-3740
48	SPL	87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583211*	183-2508
48	-	88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583602*	183-2508
48	-	89-90	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-3649	183-2508
48	-	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584218*	183-3740
48	-	92-93	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
48	-	94-95	2	113-4767 CD2 SL 6100 L	173-1670	R585035*	R585072*	413-4398	183-3740
48	ES	96	2	113-4767 CD2 SL 6100 L	173-1670	R585035*	R585072*	R586020*	183-3740
50	-	71	2	113-1397 PP2 W/COVER	173-1232	153-3408	133-0875K1	R384164*	183-4632
50	Elect Start	72	2	113-1397 PP2 W/COVER	173-1232	153-3408	133-0875K1	R384164*	183-4632
50	Manual Start	72	2	113-1397 PP2 W/COVER	R581730*	N/A	133-0875K1	N/A	183-4632
50	-	73	2	113-1397 PP2 W/COVER	173-1232	153-3408	133-0875K1	413-5776	183-4632
50	-	74-75	2	113-1397 PP2 W/COVER	173-1232	153-3408	133-0875K1	413-1742	183-4632
50	Elect Start	79-83	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	IN STATOR	413-9915	183-2366
50	Manual Start	79-82	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
50	Manual Start	84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	413-9915	183-2366
50	Elect Start	84	2	113-2453 CD2 NO LIMIT	173-1670	153-1778	133-3387	413-9915	183-2366
50	Manual Start	85	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
50	Elect Start	85	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583099*	183-2508
50	-	86-87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583211*	183-2508
50	-	88	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583602*	183-2508
50	BE, TE, TL, RN	89-90	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-3649	183-2508
50	TL	90	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-3649	183-3740
50	TE, TTL	90	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584082*	183-3740
50	TE, TTL	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584216*	183-3740
50	TL	91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584218*	183-3740
50	BE, J, Elec. St	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4686	183-3740
50	BE, M, Elec. St	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
50	TE, J	92	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4695	183-3740

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

J/E

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
50	TE, M, Elec.St	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R584216*	183-3740
50	TL, M, Elec.St	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
50	TL, J, Elec.St	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4686	183-3740
50	JE, M, Elec.St	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4398	183-3740
50	JE, J, Elec.St	92	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	413-4686	183-3740
50	EI/TL	93	2	113-4767 CD2 SL 6700L	173-1670	193-4476	133-3387	413-4686	183-3740
50	TE/TTL	93-94	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4695	183-3740
50	EL/TL	94	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4686	183-3740
50	Manual Start	95	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-3740
50	TE/TL, Elec.St	95	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4686	183-3740
50	TE/TLL, Elec.St	95	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	413-4695	183-3740
50	TTL	95	3	113-4808 CD3 AL 6700L	173-4560	193-4476	133-4804	413-4603	183-2508
50	DT/JL/EL/TL	95	3	113-4808 CD3 AL 6700L	173-4560	193-4476	133-4804	413-4401	183-2508
50	EL/TL/TTL/TE	96	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R586020*	183-3740
50	TTL	96	3	113-4808 CD3 AL 6700L	173-4560	193-4476	133-4804	R586021*	183-2508
50	DT/JL/EL/TL	95-98	3	113-4808 CD3 AL 6700L	173-4560	193-4476	133-4804	R586021*	183-2508
50	Manual Start	99	2	113-4767 CD2 SL 6100	173-1670	N/A	133-3387	N/A	183-3740
50	TTL	97	3	113-4808 CD3 AL 6700L	173-4560	193-4476	133-4804	R583601*	183-2508
50	Elect Start	97-99	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R586020*	183-3740
50	Elect Start 2 STK	00-05	2	113-5316 CD2 SL 6700L	173-4560	193-4476	133-5386	R585015*	183-3740
55	-	68	3	113-7123 BATTERY CD	173-0726	153-0705	POINTS	413-9901	183-2382
55	-	69	3	113-7123 BATTERY CD	173-0726	153-0705	POINTS	413-9902	183-2382
55	-	76-77	2	113-1397 PP2 NO LIMIT	173-1232	153-3408	133-0875K1	413-1742	183-4632
55	-	78	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	In Stator	413-9913	183-2366
55	Elect Start	79-83	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	In Stator	413-9915	183-2366
55	Manual Start	79-82	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
55	-	88	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
55	Comm	82	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
55	Comm	83-84	2	113-2474 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-2366
55	Comm	85	2	113-3241 CD2 5800 L	173-1670	N/A	133-3387	N/A	183-2508
55	Comm	86	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
55	Comm	87	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	N/A	183-2508
55	Comm, El St	89-91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	R583948*	183-2508
55	Comm, Mn St	89-91	2	113-4489 Conversion Kit	173-1670	153-1778	133-3387	N/A	183-2508
55	Comm	92-95	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-3740
55	Comm, Mn St	93-00	2	113-3241 CD2 5800L	173-1670	N/A	133-3387	N/A	183-3740
55	Comm, El St	96-97	2	113-3241 CD2 5800L	173-1670	153-1778	133-3387	413-4398	183-3740
60	VX	67	N/A	-	R580650*	153-0656	POINTS	R381626*	N/A
60	-	70-71	3	113-7123 BATTERY CD	173-0744	153-3408	POINTS	413-9903	183-2382
60	Elect Start	79-84	2	113-2453 CD2 NO LIMIT	173-1651	153-1778	133-3387	413-9915	183-2366
60	Manual Start	79-84	2	113-2453 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2366
60	Manual Start	85	2	113-2285 CD2 NO LIMIT	173-1670	N/A	133-3387	N/A	183-2508
60	Elect Start	85	2	113-2285 CD2 NO LIMIT	173-1670	153-1778	133-3387	R583099*	183-2508
60	EL/TL	86-87	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	413-3082	183-2508
60	TTL	88	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-4558	N/A	183-2508
60	EL/TL	88	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	413-3444	183-2508
60	SST	89	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	413-3771	183-2508
60	-	89	3	113-3748 CD3 SL 6700	173-4766	153-3408	133-3378	413-3771	183-2508
60	EL/TL	90	3	113-3748 CD3 SL 6700	173-4766	153-3408	133-3378	413-3771	183-2508
60	SST	90	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	413-3771	183-2508
60	TTL	90	3	113-3748 CD3 SL 6700	173-4766	153-3408	133-4558	R584155*	183-2508
60	EL/TL/TX	91	3	113-3748 CD3 SL 6700 L	173-4766	153-3408	133-3378	R584169*	183-2508
60	TTL	91	3	113-3748 CD3 SL 6700 L	173-4766	R583940*	133-4558	R584170*	183-2508
60	EL/TL/TX	92	3	113-3748 CD3 SL 6700 L	173-4560	193-4476	133-3378	413-4401	183-2508
60	TTL	92	3	113-3748 CD3 SL 6700 L	173-4560	193-4476	133-4558	413-4401	183-2508
60	EL/TL/TX	93	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4401	183-2508
60	TTL	93	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4603	183-2508
60	EL/TL/TX	94	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4401	183-2508

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
60	TTL	94	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4603	183-2508
60	EL/TL/TX	94	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4401	183-2508
60	TTL	94-95	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4603	183-2508
60	DT/JL/EL/TL	95	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4401	183-2508
60	TTL	96	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	R586021*	183-2508
60	DT/JL/EL/TL	96	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	R586021*	183-2508
60	TTL	97	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	R586021*	183-2508
60	-	97-01	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	R586021*	183-2508
65	-	68	3	113-7123 BATTERY CD	173-0726	153-0705	POINTS	413-9904	183-2382
65	-	72	3	113-1726 PP3/6 W/Cover	173-1235	153-3408	133-1251	413-9912	183-2303
65	-	73	3	113-1726 PP3/6 W/Cover	173-1235	153-3408	133-1251	413-9916	183-2303
65	-	89	3	113-3748 CD3 SL 6700 L	173-4766	153-3408	133-3378	413-3771	183-2508
65	Jet	95	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
65	Comm,Man.Strt	84	3	113-2556 CD3/6 5800 L	173-4766	N/A	133-3378	N/A	183-2366
65	Comm	84-85	3	113-2556 CD3/6 5800 L	173-3724	153-3408	133-3378	R394508*	183-2366
65	Comm	86	3	113-3122 CD3/6 5800 L	173-3724	153-3408	133-3378	413-3082	183-2508
65	Comm	87	3	113-3122 CD3/6 5800 L	173-3724	153-3408	133-3378	R582756*	183-2508
65	Comm	88	3	113-3122 CD3/6 5800 L	173-3724	153-3408	133-3378	R583559*	183-2508
65	Comm,Man.Strt	89-90	3	113-3748 CD3 SL 6700 L	173-4766	153-3408	133-4558	N/A	183-2508
65	Comm,Elec.Strt	89-90	3	113-3748 CD3 SL 6700 L	173-4766	153-3408	133-3378	413-3771	183-2508
65	Comm,Elec.Strt	90	3	113-3748 CD3 SL 6700 L	173-4766	153-3408	133-3378	413-3771	183-2508
65	Comm,Elec.Strt	91	3	113-3748 CD3 SL 6700 L	173-4766	153-3408	133-3378	R584169*	183-2508
65	Comm,Man.Strt	91-95	3	113-3748 CD3 SL 6700 L	173-4766	R583940*	133-4558	N/A	183-2508
65	Comm,Man.Strt.	92-95	3	113-3748 CD3 SL 6700 L	173-4766	N/A	133-4558	N/A	183-2508
65	Comm,Elec.Strt.	92	3	113-3748 CD3 SL 6700 L	173-4560	193-4476	133-4558	413-4401	183-2508
65	Comm,Elect.Strt.	93-94	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4401	183-2508
65	Comm W/O VRO	95	3	113-3748 CD3 SL 6700 L	173-4766	193-4476	133-4558	413-4401	183-2508
65	Comm W/VRO	95	3	113-4808 CD3 AL 6700 L	173-4560	193-4476	133-4804	413-4401	183-2508
65	Comm	96-00	3	R585274* CD3 SL2 6700L	173-4560	193-4476	133-3378	R586021*	183-2508
70	-	73	3	113-1726 PP3/6 W/Cover	173-1235	153-3408	133-1251	413-9916	183-2303
70	-	74-77	3	113-1726 PP3/6 W/Cover	173-1235	153-3408	133-1251	413-1886	183-2303
70	-	78	3	113-1726 PP3/6 W/Cover	173-1235	153-3408	133-1251	R581974*	183-2303
70	-	79-84	3	113-2138 CD3/6 NO LMT	173-3724	153-3408	133-3378	413-1377	183-2366
70	-	85	3	113-2705 CD3/6 NO LMT	173-3724	153-3408	133-3378	R395186*	183-2508
70	EL/TL W/O Trim	86	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	R582756*	183-2508
70	EL/TL W/Trim	86	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	R582970*	183-2508
70	EL/TL W/O Trim	87	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	R582756*	183-2508
70	EL/TL W/Trim	87	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	R582970*	183-2508
70	W/O Trim	88	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	R583559*	183-2508
70	W/Trim	88	3	113-2115 CD3/6 NO LMT	173-3724	153-3408	133-3378	413-3560	183-2508
70	-	89-90	3	113-3748 CD3 SL 6700	173-4766	153-3408	133-3378	413-3771	183-2508
70	EL/TL/TX	91	3	113-3748 CD3 SL 6700	173-4766	153-3408	133-3378	R584169*	183-2508
70	TTL	91	3	113-3748 CD3 SL 6700	173-4766	R583940*	133-4558	R584170*	183-2508
70	EL/TL/TX	92	3	113-3748 CD3 SL 6700	173-4560	193-4476	133-3378	413-4401	183-2508
70	TTL	92	3	113-3748 CD3 SL 6700	173-4560	193-4476	133-4558	413-4401	183-2508
70	EL/TL/TX	93	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	413-4401	183-2508
70	TTL	93	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	413-4603	183-2508
70	EL/TL/TX	94	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	413-4401	183-2508
70	TTL C & S	94	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	413-4603	183-2508
70	EL/TL/TX	94	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	413-4401	183-2508
70	TTL	94-95	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	413-4603	183-2508
70	DT/JL/EL/TL	95	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	413-4401	183-2508
70	DT/JL/EL/TL	96	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	R586021*	183-2508
70	RNLB	96	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	R586021*	183-2508
70	-	97-01	3	113-4808 CD3 AL 6700	173-4560	193-4476	133-4804	R586021*	183-2508
75	-	65-66	3	N/A	N/A	R380076	POINTS	413-9900	N/A
75	-	75-77	3	113-1726 PP3/6 W/Cover	173-1235	153-3408	133-1251	413-1886	183-2303
75	-	78	3	113-1726 PP3/6 W/Cover	173-1235	153-3408	133-1251	R581974*	183-2303
75	-	79-84	3	113-2138 CD3/6 NO LIMIT	173-3724	153-3408	133-3378	413-1377	183-2366

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

J/E

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
75	-	85	3	113-2705 CD3/6 NO LIMIT	173-3724	153-3408	133-3378	R395186*	183-2508
75	EC	86-87	3	113-2115 CD3/6 NO LIMIT	173-3724	153-3408	133-3378	413-3082	183-2508
75	-	88	3	113-2115 CD3/6 NO LIMIT	173-3724	153-3408	133-3378	R583444*	183-2508
80	SPEEDIFOUR	67	4	N/A	R580650*	153-0656	POINTS	R381645*	N/A
80	STARFLITE	67	4	N/A	N/A	R380076	POINTS	R381638*	N/A
80	Jet	92	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
80	Jet	93-94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
80	Jet Tiller	95	4	113-4030 CD4/8 5800 L	173-3536	R583940*	133-3379	R584356*	183-2508
80	Jet	96	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-6027	183-2508
80	Jet	2000	4	113-6292 CD4 OPTICAL	173-4849	193-6048	133-6343	413-4762	N/A
85	JET 115 JLE	97	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-6027	183-2508
85	V4S SPEEDI 4	68	4	113-7123 BATTERY CD	173-0726	153-0705	POINTS	413-9910	183-2382
85	V4A STARFLITE	68	4	113-7123 BATTERY CD	173-0726	153-0705	POINTS	413-9905	183-2382
85	-	69	4	113-7123 BATTERY CD	173-0744	153-0705	POINTS	413-9906	183-2382
85	-	70-72	4	113-7123 BATTERY CD	173-0744	153-3408	POINTS	413-9907	183-2382
85	6 Amp	73	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-5501	183-4632
85	12 Amp	73	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-5501	183-4632
85	6 Amp	74-76	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-9918	183-4632
85	12 Amp	74-76	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-9918	183-4632
85	6 Amp	77	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-1721	183-4632
85	12 Amp	77	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-1721	183-4632
85	-	78-79	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-1975	183-2366
85	-	80-82	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-2161	183-2366
85	-	83	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	R393290*	183-2366
85	TTL	91	4	113-4028 CD4/8 NO LIMIT	173-3536	R583940*	133-3379	R584356*	183-2508
85	TTL	92-95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	R584604*	183-2508
85	TTL W/O Trim	94	4	113-4030 CD4/8 5800 L	173-3536	R583940*	133-3379	413-4390	183-2508
85	TTL W/Trim	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
85	TTL	95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	R584356*	183-2508
88	-	87	4	113-3110 CD4 NO LIMIT	173-3672	153-3408	133-3379	413-5253	183-2508
88	-	88	4	113-3101 CD4 6700 L	173-3536	153-3408	133-3379	413-4004	183-2508
88	W/O Trim	89-91	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-4004	183-2508
88	W/Trim	89-91	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4004	183-2508
88	-	92-93	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	R584389*	183-2508
88	W/O Trim	94	4	113-4030 CD4/8 5800 L	173-3536	153-3408	133-3379	R584389*	183-2508
88	W/Trim	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	R584389*	183-2508
88	TS W/20 IN	94-95	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	R584389*	183-2508
88	TS W/25 IN	94-95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
88	MS	95-96	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	R584389*	183-2508
88	TS W/20 IN	96	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-6027	183-2508
88	TS W/25 IN	96	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-6027	183-2508
90	6 Amp	84	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-4495	183-2366
90	10 Amp	84	4	113-2125 CD4 NO LIMIT	173-3672	193-5204	133-3376	413-4495	183-2366
90	W/O Trim	85	4	113-2811 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-4495	183-2508
90	W/Trim	85	4	113-2811 CD4 NO LIMIT	173-3672	193-5204	133-3376	413-4495	183-2508
90	W/O Trim	86-87	4	113-3110 CD4 NO LIMIT	173-3672	153-3408	133-3376	R583036*	183-2508
90	W/Trim	86-87	4	113-3110 CD4 NO LIMIT	173-3672	193-5204	133-3376	R583036*	183-2508
90	-	88	4	113-3101 CD4 6700 L	173-3536	153-3408	133-3379	413-4004	183-2508
90	W/O Trim	89-90	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-4004	183-2508
90	W/Trim	89-90	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4004	183-2508
90	-	91	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	R584211*	183-2508
90	-	92-93	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
90	W/O Trim	94	4	113-4030 CD4/8 5800 L	173-3536	153-3408	133-3379	413-4390	183-2508
90	W/Trim	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
90	JE TurboJet	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
90	JLE	95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
90	TurboJet	95	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
90	EL/EX/SL,60 Deg	95	4	113-6292 CD4 OPTICAL	173-4849	193-4847	133-6343	413-5085	183-3740
90	20 IN	96-97	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-6027	183-2508

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
90	25 IN	96-97	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-6027	183-2508
90	60 Deg	96-05	4	113-6292 CD4 OPTICAL	173-4849	193-6048	133-6343	413-4762	183-3740
100	-	65-66	4	N/A	N/A	193-0076	POINTS	413-9900	N/A
100	Starflite	67	4	113-8362 BATTERY CD	R580648*	153-3408	R580668*	413-9908	183-2382
100	Starflite	68	4	113-8362 BATTERY CD	173-0725	153-3408	133-5008	413-9909	183-2382
100	W/Alt	68	4	N/A	N/A	N/A	POINTS	413-9911	N/A
100	-	71	4	113-7123 BATTERY CD	173-0744	153-3408	POINTS	413-9907	183-2382
100	-	72	4	113-8362 BATTERY CD	173-0744	153-3408	133-5008	413-9907	183-2382
100	W/O Trim	90	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-4004	183-2508
100	W/Trim	90	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4004	183-2508
100	-	91	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	R584211*	183-2508
100	-	92-93	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
100	W/O Trim	94	4	113-4030 CD4/8 5800 L	173-3536	153-3408	133-3379	413-4390	183-2508
100	W/Trim	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
100	Comm	84	4	113-2684 CD4 5700 L	173-3672	193-5204	133-3376	413-4495	183-2366
100	Comm	85	4	113-2704 CD4 5700 L	173-3672	193-5204	133-3376	413-5253	183-2508
100	Comm	86	4	113-3116 CD4 5700 L	173-3672	193-5204	133-3376	R583036*	183-2508
100	Comm	87	4	113-3116 CD4 5700 L	173-3672	153-3408	133-3376	R583036*	183-2508
100	Comm	88	4	113-3101 CD4 6700 L	173-3536	193-4204	133-3379	413-4004	183-2508
100	Comm	89	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4004	183-2508
100	Comm,W/O Trim	90	4	113-4030 CD4/8 5800 L	173-3536	153-3408	133-3379	413-4004	183-2508
100	Comm,W/Trim	90	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4004	183-2508
100	Comm	91	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	R584211*	183-2508
100	Comm	92-93	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
100	Comm WM	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	R584389*	183-2508
100	Comm WT	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
100	Comm WT/WL	95	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
100	Comm	96-97	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-6027	183-2508
100	Comm	2000	4	113-6292 CD4 OPTICAL	173-4849	193-6048	133-6343	413-4762	183-3740
105	Jet W/O VRO	94	6	113-4985 OPTICAL	173-4981	193-4093	133-6343	R584579*	183-2508
105	Jet W/VRO	94	6	113-4985 OPTICAL	173-4981	193-4093	133-6343	R584674*	183-2508
105	Jet	2000	6	113-4985 OPTICAL	173-4981	193-6048	133-6343	R586028*	183-2508
105	Comm,Man.Star	2000	4	113-6292 CD4 OPTICAL	173-4849	193-6048	133-6343	N/A	183-3740
105	Comm WE	2000	4	113-6292 CD4 OPTICAL	173-4849	193-6048	133-6343	R586332*	183-3740
105	Comm WP	2000	4	113-6292 CD4 OPTICAL	173-4849	193-6048	133-6343	413-4762	183-3740
110	W/O Trim	86-87	4	113-3110 CD4 NO LIMIT	173-3672	153-3408	133-3376	R583036*	183-2508
110	W/Trim	86-87	4	113-3110 CD4 NO LIMIT	173-3672	193-5204	133-3376	R583036*	183-2508
110	TLCDF,W/O Trim	86	4	113-2811 CD4 NO LIMIT	173-3672	153-3408	133-3376	R583036*	183-2508
110	TLCDF W/Trim	86	4	113-2811 CD4 NO LIMIT	173-3672	193-5204	133-3376	R583036*	183-2508
110	W/O Trim	88	4	113-3101 CD4 6700 L	173-3536	153-3408	133-3379	413-4004	183-2508
110	W/Trim	88	4	113-3101 CD4 6700 L	173-3536	153-3408	133-3379	413-4004	183-2508
110	W/O Trim	89	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-4004	183-2508
110	W/Trim	89	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4004	183-2508
112	20 IN	94-95	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	R584389*	183-2508
112	25 IN	94-95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
112	20 IN	96	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-6027	183-2508
112	25 IN	96	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-6027	183-2508
115	-	69	4	113-8362 BATTERY CD	173-0744	153-3408	133-5008	413-9906	183-2382
115	-	70	4	113-8362 BATTERY CD	173-0744	153-3408	133-5008	413-9907	183-2382
115	6 Amp	73	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-5501	183-4632
115	12 Amp	73	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-5501	183-4632
115	6 Amp	74-76	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-9918	183-4632
115	12 Amp	74-76	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-9918	183-4632
115	6 Amp	77	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-1721	183-4632
115	12 Amp	77	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-1721	183-4632
115	-	78-79	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-1975	183-2366
115	-	80-82	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-2161	183-2366
115	-	83	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	R393290*	183-2366
115	6 Amp	84	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-4495	183-2366
115	10 Amp	84	4	113-2125 CD4 NO LIMIT	173-3672	193-5204	133-3376	413-4495	183-2366

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

J/E

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
115	W/O Trim	85	4	113-2811 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-5253	183-2508
115	W/Trim	85	4	113-2811 CD4 NO LIMIT	173-3672	193-5204	133-3376	413-5253	183-2508
115	W/O Trim	90	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-4004	183-2508
115	W/Trim	90	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4004	183-2508
115	W/O Trim	91	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	R584211*	183-2508
115	W/Trim	91	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	R584211*	183-2508
115	W/O Trim	92-93	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
115	W/Trim	92-93	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
115	W/O Trim	94	4	113-4030 CD4/8 5800 L	173-3536	153-3408	133-3379	413-4390	183-2508
115	W/Trim	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
115	JKL W/O Trim	94	4	113-4030 CD4/8 5800 L	173-3536	R583940*	133-3379	413-4390	183-2508
115	JKL W/Trim	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
115	JE TurboJet	94	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
115	ML/TL/TX,W/OTrim	95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
115	ML/TL/TX,W/Trim	95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
115	JLE W/O Trim	95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
115	JLE W/Trim	95	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-4390	183-2508
115	JKL 80 Jet	95	4	113-4028 CD4/8 NO LIMIT	173-3536	R583940*	133-3379	R584356*	183-2508
115	60 Deg	95	4	113-6292 CD4 OPTICAL	173-4849	193-4847	133-6343	413-5085	183-3740
115	-	96	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-6027	183-2508
115	TurboJet	96	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
115	60 Deg	96	4	113-6292 CD4 OPTICAL	173-4849	193-6048	133-6343	413-4762	183-3740
115	20 IN	97	4	113-4028 CD4/8 NO LIMIT	173-3536	153-3408	133-3379	413-6027	183-2508
115	25 IN	97	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	413-6027	183-2508
115	TurboJet	97	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4390	183-2508
115	60 Deg	97-05	4	113-6292 CD4 OPTICAL	173-4849	193-6048	133-6343	413-4762	183-3740
120 -	-	85	4	113-3072 CD4 6100 L	173-3669	193-2907	133-3379	413-3590	183-2508
120	-	86-87	4	113-3101 CD4 6700 L	173-3669	193-2907	133-3379	413-3145	183-2508
120	LOOPER	88-90	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-3284	183-2508
120	LOOPER	92-94	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-4406	183-2508
125	-	71-72	4	113-8362 BATTERY CD	173-0744	153-3408	133-5008	413-9907	183-2382
125	-	91	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	R584183*	183-2508
125	-	92-94	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-4406	183-2508
125	Comm,Man,St	89-94	4	113-4032 CD4AL 6700 L	173-4821	N/A	133-3379	N/A	183-2508
125	Comm,Elec.St	89-93	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-3284	183-2508
125	Comm,Elec.St	94-95	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-4406	183-2508
130	-	94-95	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-4406	183-2508
130	-	96-00	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	R586022*	183-2508
135	6 Amp	73	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-5501	183-4632
135	12 Amp	73	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-5501	183-4632
135	6 Amp	74-76	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-9918	183-4632
135	12 Amp	74-76	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-9918	183-4632
140	6 Amp	77	4	113-1731 PP4 W/Cover	173-1225	153-3408	133-1900	413-1721	183-4632
140	12 Amp	77	4	113-1731 PP4 W/Cover	173-2099	153-3408	133-1900	413-1721	183-4632
140	-	78-79	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-1975	183-2366
140	-	80-82	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-2161	183-2366
140	-	83	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	R393290*	183-2366
140	6 Amp	84	4	113-2125 CD4 NO LIMIT	173-3672	153-3408	133-3376	413-4495	183-2366
140	10 Amp	84	4	113-2125 CD4 NO LIMIT	173-3672	193-4204	133-3376	413-4495	183-2366
140	-	85	4	113-3072 CD4 6700 L	173-3669	193-2907	133-3379	413-3590	183-2366
140	-	86-87	4	113-3101 CD4 6700 L	173-3669	193-2907	133-3379	413-3145	183-2508
140	LOOPER	88-90	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-3284	183-2508
140	LOOPER	91	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	R584183*	183-2508
140	LOOPER	92-93	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-4406	183-2508
140	LOOPER	94	4	113-4041 CD4AL 6700 L	173-3410	193-4205	133-3508	413-4406	183-2508
150	-	78	6	113-1726 PP3 W/COVER	173-1867	153-3408	133-1486	413-9917	183-2303
150	-	79-83	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
150	TL/TX	84	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
150	AN/ST,10 Amp	84	6	113-2138 CD3/6NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
150	AN/ST, 35 Amp	84	6	113-2138 CD3/6 NO LIMIT	173-3668	193-5204	133-3377	413-2866	183-2366

* Indicates an item available on a Repair & Return basis at this time.

** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

J/E

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
150	TL/TX	85	6	113-2651 CD3/6 5800 L	173-3672	193-5204	133-3377	413-2915	183-2508
150	ST , 10 Amp	85	6	113-2651 CD3/6 5800 L	173-3672	193-5204	133-3377	413-2915	183-2508
150	ST , 35 Amp	85	6	113-2651 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2915	183-2508
150	TL/TX 10 Amp	86-87	6	113-3114 CD3/6 5800 L	173-3672	193-5204	133-3377	413-3035	183-2508
150	ST, 35 Amp	86-87	6	113-3114 CD3/6 5800 L	173-3668	193-5204	133-3377	413-3035	183-2508
150	TL/TX	88	6	113-3114 CD3/6 5800 L	173-3537	193-4204	133-3377	R583294*	183-2508
150	ST, 35 Amp	88	6	113-3114 CD3/6 5800 L	173-3668	193-5204	133-3377	R583294*	183-2508
150	TL/TX	89	6	R584044* CD6SL 5800 L	173-3837	193-4204	N/A	R584016*	183-2508
150	SL/ST	89-90	6	113-3865 CD6AL 5800 L	173-4292	193-5204	133-3853	413-3852	183-2508
150	TL/TX	90	6	R584044* CD6SL 5800 L	173-3837	193-4204	N/A	R584016*	183-2508
150	ST	90	6	113-3865 CD6AL 5800 L	173-4292	193-5204	133-3853	413-3852	183-2508
150	GL/EL/EX/NX 60°	91	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-2508
150	TL/TX/CX/JL	91	6	R584044* CD6SL 5800 L	173-3837	193-4204	N/A	R584220*	183-2508
150	SL/ST	91	6	113-3865 CD6AL 5800 L	173-4292	193-5204	133-3853	413-4221	183-2508
150	-	92	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
150	-	93	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
150	W/O VRO	94	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	R584579*	183-3740
150	W/VRO	94	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
150	-	95	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
150	-	96-05	6	113-4985 CD6AL 6100 L	173-4981	193-6048	133-6343	R586028*	183-3740
150	Comm,W/O VRO	93	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	R584579*	183-3740
150	Comm, W/VRO	93	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
150	Comm, W/O VRO	95	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	R585251*	183-3740
150	Comm, W/VRO	95	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
150	Comm	2000	6	113-4985 CD6AL 6100 L	173-4981	193-6048	133-6343	R586028*	183-3740
155	Comm, 35 Amp	84	6	113-2138 CD3/6 NO LIMIT	173-3668	193-5204	133-3377	413-2866	183-2366
155	Comm	85	6	113-2651 CD3/6 5800 L	173-3668	193-5204	133-3377	R582915*	183-2508
155	Comm	86-87	6	113-3114 CD3/6 5800 L	173-3668	193-5204	133-3377	413-3035	183-2508
155	Comm	88	6	113-3114 CD3/6 5800 L	173-3668	193-5204	133-3377	R583294*	183-2508
155	Comm, 10 Amp	89-90	6	R584044* CD6SL 5800 L	173-3837	193-4204	N/A	R584016*	183-2508
155	Comm, 35 Amp	89-90	6	113-3865 CD6AL 5800 L	173-4292	193-5204	133-3853	R584016*	183-2508
155	Comm	91	6	113-3865 CD6AL 5800 L	173-4292	193-5204	133-3853	413-4221	183-2508
155	Comm	92	6	113-3865 CD6AL 5800 L	173-4292	193-5204	133-3853	R584414*	183-2508
175	-	77-78	6	113-1726 PP3/6 W/Cover	173-1867	153-3408	133-1486	413-9917	183-2303
175	-	79-83	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2508
175	TL/TX	85	6	113-2651 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2915	183-2508
175	TL/TX	86-87	6	113-3114 CD3/6 5800 L	173-3668	193-5204	133-3377	413-3035	183-2508
175	TL/TX/ST	88	6	113-3114 CD3/6 5800 L	173-3537	193-5204	133-3377	R583294*	183-2508
175	-	89-90	6	113-3865 CD6AL 5800 L	173-4292	193-5204	133-3853	413-3852	183-2508
175	GL/EL/EX/NX/TX	91	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
175	105 Jet	92-93	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
175	W/O VRO	94	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	R584579*	183-3740
175	W/VRO	94	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
175	GL/EL/EX/NX/TX	96-05	6	113-4985 CD6AL 6100 L	173-4981	193-6048	133-6343	R586028*	183-3740
175	105 Jet	95	6	113-4985 CD6AL 6100 L	173-4981	193-4093	133-6343	413-5240	183-3740
175	105 Jet	96-98	6	113-4985 CD6AL 6100 L	173-4981	193-6048	133-6343	R586028*	183-3740
185	-	77-78	6	113-1726 PP3/6 W/Cover	173-1867	153-3408	133-1486	413-9917	183-2303
185	-	79-83	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
185	TL/TX	84	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
185	TL/TX	85	6	113-2651 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2915	183-2508
185	-	90	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-3282	183-2508
185	-	91	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-4171	183-2508
185	-	92	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-4404	183-2508
185	-	93-94	6	113-6212 CD6AL 6700 L	173-4643	193-4641	133-3533	413-4645	183-2508
200	-	76-78	6	113-1726 PP3/6 W/Cover	173-1867	153-3408	133-1486	413-9917	183-2366

* Indicates an item available on a Repair & Return basis at this time.
 ** Indicates an item not available from CDI/RAPAIR at this time.



JOHNSON/EVINRUDE APPLICATION GUIDE

J/E

Application Guide (Cont.)

Johnson/Evinrude Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
200	-	79-83	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
200	-	86-87	6	113-3605 CD3/6 6200 L	173-3117	193-3689	133-3048	413-3047	183-2508
200	-	88-90	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-3282	183-2508
200	-	91	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-4171	183-2508
200	-	92	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-4404	183-2508
200	-	93-94	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	413-4645	183-2508
200	-	95	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	413-5241	183-2508
200	-	96	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	R586023*	183-2508
200	-	97-99	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	R586023*	183-2508
200	-	2000	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	R586243*	183-2508
200	Comm	94	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	413-4645	183-2508
200	Comm	2000	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	R586243*	183-2508
225	-	86-87	6	113-3605 CD3/6 6200 L	173-3117	193-5204	133-3048	413-3047	183-2508
225	-	88-90	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-3282	183-2508
225	-	91	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-4171	183-2508
225	-	92	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	413-4404	183-2508
225	-	93-94	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	413-4645	183-2508
225	-	95	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	413-5241	183-2508
225	-	96	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	R586023*	183-2508
225	-	97-99	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	R586023*	183-2508
225	-	2000	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	R586243*	183-2508
235	-	78	6	113-1726 PP3/6 NO LIMIT	173-1867	153-3408	133-1486	413-9917	183-2303
235	-	79	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
235	-	80-83	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
235	ST.PORT,10 Amp	84	6	113-2138 CD3/6 NO LIMIT	173-3672	193-5204	133-3377	413-2866	183-2366
235	ST.STBD,10 Amp	84	6	113-2556 CD3/6 5800 L	173-3672	193-5204	133-3377	413-2866	183-2366
235	ST.PORT,35 Amp	84	6	113-2138 CD3/6 NO LIMIT	173-3668	193-5204	133-3377	413-2866	183-2366
235	ST.STBD,35 Amp	84	6	113-2556 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2866	183-2366
235	TL/TX	85	6	113-2651 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2915	183-2508
235	ST, 10 Amp	85	6	113-2537 CD3/6 5800 L	173-3672	193-5204	133-3377	413-2915	183-2508
235	ST, 35 Amp	85	6	113-2537 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2915	183-2508
250	-	91-92	8	113-4035 CD8AL 6700 L	173-4287	193-3689	**583531	R584224*	183-2508
250	-	93-94	8	113-4642 CD8AL 6700 L	173-4643	193-4641	**583531	413-2866	183-2508
250	-	95	8	113-4642 CD8AL 6700 L	173-4643	193-4641	**583531	R585242*	183-2508
250	-	97	8	113-4642 CD8AL 6700 L	173-4643	193-4641	**583531	R586024*	183-2508
250	-	2000	6	113-6212 CD6AL 6700	173-4643	193-4641	133-3533	R586243*	183-2508
275	-	85	8	113-3072 CD4 6700 L	173-3117	193-3689	**583375	R391483*	183-2508
275	3.6L	86-87	8	113-3101 CD4/8 6100L	173-3117	193-3689	**583375	R583033*	183-2508
275	-	88-89	8	113-4035 CD8AL 6700 L	173-4287	193-3689	**583531	R583283*	183-2508
300	3.6L	85	8	113-3072 CD4 6700 L	173-3117	193-3689	**583375	R391483*	183-2508
300	3.6L	86-87	8	113-3101 CD4/8 6100L	173-3117	193-3689	**583375	R583033*	183-2508
300	-	88-89	8	113-4035 CD8AL 6700 L	173-4287	193-3689	**583531	R583283*	183-2508
300	-	90	8	113-4035 CD8AL 6700 L	173-4287	193-3689	**583531	R583283*	183-2508
300	-	91-92	8	113-4035 CD8AL 6700 L	173-4287	193-3689	**583531	R584224*	183-2508
300	-	93-94	8	113-4642 CD8AL 6700 L	173-4287	193-4641	**583531	R584886*	183-2508

See Next Page For SeaDrive Cross Reference

* Indicates an item available on a Repair & Return basis at this time.
 ** Indicates an item not available from CDI/RAPAIR at this time.



Application Guide

OMC (SeaDrive) Application Guide

HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
Sea Drive									
2.5 L	-	82	6	113-2138 CD3/6 NO LIMIT	173-3672	153-3408	133-3377	413-9452	183-2366
2.6 L	-	82	6	113-2138 CD3/6 NO LIMIT	173-3672	153-3408	133-3377	413-9452	183-2366
1.6 L	-	83	8	113-2125 CD4/8 NO LIMIT	173-3672	153-3408	133-3376	R393290*	183-2366
2.6 L	1AA/2BA/2BB, 10Amp	83	6	113-2556 CD3/6 5800 L	173-3672	153-3408	133-3377	R582586*	183-2366
2.6L	1AA/2BA/2BB, 35Amp	83	6	113-2138 CD3/6 NO LIMIT	173-3668	193-5204	133-3377	R393603*	183-2366
1.6 L	S V4	84	4	113-2125 CD4/8 NO LIMIT	173-3672	193-5204	133-3376	413-4495	183-2366
2.5 L	-	84	6	113-2556 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2866	183-2366
2.6 L	-	84	6	113-2556 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2866	183-2366
1.6 L	-	85	4	113-2811 CD4/8 NO LIMIT	173-3672	193-5204	133-3376	413-5253	183-2508
2.5 L	-	85	6	113-2651 CD3/6 AL 5800	173-3668	193-5204	133-3377	413-2915	183-2508
2.6 L	-	85	6	113-2651 CD3/6 AL 5800	173-3668	193-5204	133-3377	413-2915	183-2508
1.6 L	-	86	4	113-3110 CD4/8 NO LIMIT	173-3104	193-5204	133-3376	R583036*	183-2508
2.6 L	-	86	6	113-3114 CD3/6 5800 L	173-3668	193-3689	133-3377	R583035*	183-2508
1.6 L	-	87	4	113-3110 CD4/8 NO LIMIT	173-3104	193-5204	133-3376	R984733*	183-2508
1.8 L	-	87	4	113-3101 CD4/8 AL 6100	173-4291	193-3689	133-3379	R583135*	183-2508
2.7 L	-	87	6	113-3605 CD3/6 AL 6200	173-3668	193-3689	133-3048	R583179*	183-2508
3.6 L	-	87	8	113-3101 CD4/8 AL 6100	173-3117	193-3689	**583148	R583181*	183-2508
1.6 L	-	88	4	113-3101 CD4/8 AL 6100	173-3536	193-4204	133-3379	R986537*	183-2508
2.0 L	-	88	4	113-4041 CD4AL 6700 L	173-4288	193-3689	133-3508	R583596*	183-2508
3.0 L	-	88	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	R583597*	183-2508
1.6 L	-	89	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	R986537*	183-2508
2.0 L	-	89	4	113-4041 CD4AL 6700 L	173-4288	193-3689	133-3508	R583596*	183-2508
3.0 L	-	89	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	R583597*	183-2508
4.0 L	-	89	8	113-4035 CD8AL 6700 L	173-4287	193-3689	**583531	R583598*	183-2508
1.6 L	-	90	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	R986537*	183-2508
2.0 L	-	90	4	113-4041 CD4AL 6700 L	173-4288	193-3689	133-3508	R583596*	183-2508
3.0 L	-	90	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	R583597*	183-2508
4.0 L	-	90	8	113-4035 CD8AL 6700 L	173-4287	193-3689	**583531	R583598*	183-2508
Battery CDI Ignition Systems									
HP	YEAR	CD. IGN	TYPE	STATOR	IGN. COIL	SENSOR	REG./RECT		
55	'68-'69	113-7123	6CB2007	173-0726 ⁹	183-2382	Points	153-0705		
60	'70-'71	113-7123	6CB2001	173-0744 ⁹	183-2382	Points	153-3408		
65-85	'68	113-7123	6CB2009	173-0726 ⁹	183-2382	Points	153-0705		
85	'69-'72	113-7123	6CB2004	173-0744 ⁹	183-2382	Points	153-3408		
100	'67	113-8362	IDG3001A	R580648 ¹⁵	183-2382	*R580668	153-3408		
100	'68	113-8362	IDG3001B	173-0725 ¹⁵	183-2382	133-5008	153-3408		
100	'71	113-7123	6CB2004	173-0744 ⁹	183-2382	Points	153-3408		
100	'72	113-8362	IDG3001	173-0744 ⁹	183-2382	133-5008	153-3408		
115	'69-'70	113-8362	IDG3001C	173-0744 ⁹	183-2382	133-5008	153-3408		
125	'71-'72	113-8362	IDG3001	173-0744 ⁹	183-2382	133-5008	153-3408		
Power Pack Type Ignitions (Terminal Block)									
50-55	'71-'77	113-1397	PP2	173-1232 ⁶	183-2091	133-0875K1	153-3408		
65-75	'72-'78	113-1726	PP3	173-1235 ⁶	183-2303	133-1251	153-3408		
85-140(v-4)	'73-'77	113-1731	PP4	173-1225 ⁶	183-4632	133-1900	153-3408		
150-200(v-6)	'76-'77	113-1726	PP3/6	173-1867 ⁹	183-2303	Points	153-3408		
CD Type Ignitions 1977-1984 (Non-Limited)									
6-35	'77-'84	113-2453	CD2	173-1651 (E) 173-1670 (coil only)	183-2366	In Stator 133-3387 (Manual St)	153-1778 N/A		
50-60	'78-'84	113-2453	CD2	173-1651 ¹⁵	183-2366	In Stator	153-1778		
40-60	'83-'84	113-2453	CD2	173-1670 (coil only)	183-2366	133-3387	153-1778		
70-75	'79-'84	113-2138	CD3/6	173-3724 ⁹	183-2366	133-3387	153-3408		
85-90-100- 115-140 (v4)	'78-'84	113-2125	CD4	173-3672 ⁹	183-2366	133-3376	153-3408		
150-175- 185-200- 235 (V6)	'79-'84	113-2138	CD3/6	173-3672 ⁹ 173-3668 ³⁵	183-2366	133-3377	193-5204		

(a) = 3/8" Linkage Hole (E) = Electric Start (CHG) = Charging R&R = Repair and Return * = Repair and Return
 (b) = 1/2" Ball Socket (M) = Manual Start NA = Not available from CDI Not Appl. = Not required part ** = Not available from